

Domtech Inc. 40 East Davis Street Trenton, Ontario Canada, K8V 6S4 Ph: 613-394-4884

Fax: 613-394-5372 Toll Free: 888-278-8258 www.domtech.net

ELECTRONICS COMMUNICATIONS CABLES FT4 - CMG, CM, CMX Outdoor 300V; AWM I/II A/B 600V

Applications: Commercial grade, general purpose communications cable. Available shielded or unshielded.

For use in Class 2 communication circuits when exposed, concealed, or used in raceways; Outdoor overhead in wet, dry or damp locations. Marked sunlight resistant "SUN RES" in all colours. For installation in accordance with CE Code Part 1, and Article 800 of the NEC/ANSI/NFPA 70.

Conductors: Stranded tinned copper

Insulation: Semi-Rigid Polyvinyl chloride (SRPVC)

Jacket: Polyvinyl chloride (PVC)

Voltage Rating: CMG, CM, CMX 300V; AWM I/II A/B 600V

Temperature Rating: -20°C* to 105°C

Flame Rating: FT1/FT4/VW-1/UL 1685 (Vertical Flame Tray Test)

Standards: CSA C22.2 No. 214 & 210, UL444

UNSHIELDED

Gauge	Strand	Conductor	Nominal Insulation Thickness		Nominal Jacket Thickness		Nominal Cable Diameter		Nominal Cable Weight	
AWG	Count	Count	mm	in.	mm	in.	mm	in.	kg/km	lb/mft
18	16	2	0.20	0.008	0.38	0.015	4.19	0.165	25.5	17.1
18	16	3	0.20	0.008	0.38	0.015	4.45	0.175	35.5	23.9
18	16	4	0.20	0.008	0.38	0.015	4.88	0.192	44.2	29.7

SHIELDED1

Gauge	Strand	Conductor	Nominal Insulation Thickness		Nominal Jacket Thickness		Nominal Cable Diameter		Nominal Cable Weight	
AWG	Count	Count	mm	in.	mm	in.	mm	in.	kg/km	lb/mft
18	16	2	0.20	0.008	0.38	0.015	4.19	0.165	31.1	20.9
18	16	3	0.20	0.008	0.38	0.015	4.45	0.175	41.9	28.2
18	16	4	0.20	0.008	0.38	0.015	4.88	0.192	49.9	33.5

Notes: All dimensions are nominal and are subject to normal manufacturing tolerance. Specifications are subject to change without notice. ¹Aluminum/Mylar shield with 20AWG (7X.0126) soft tinned copper drain wire.

^{*} The -20°C low temperature rating indicates that the cables have passed a cold bend test under carefully controlled laboratory conditions. These conditions may or may not reflect actual field conditions. It is therefore recommended that all cables be warmed to at least 10°C before installation.